

Please read before using this equipment.

1. Connection of the telephone

Plug in the handset and line cords.

2. MF/DP switch

Before using your telephone, it must be set in accordance with the dialing method used by your local public telephone exchange:

MF=dual-tone multi-frequency dialing (DTMF), or DP=pulse dialing

3. Volume control for receiver

3 positions: L=low; M=middle; H=high

4. Volume control for ringer

2 positions: L=low; H=high

5. Temporary switchover of the dialing mode

After a connection has been set up to use PULSE dialing, switch over to TONE dialing can be made by pressing the button *, and certain services offered by certain public telephone exchanges or PABXs, e.g. control of a telephone answering system, simple data traffic, etc., can then be utilized by dialing additional digits. When using the button * to enter digits in DTMF mode, it may take about 3 seconds to begin dialing the number. The telephone is automatically reset to PULSE dialing when handset is cradled.

6. Flash

With certain public telephone exchanges or private PABXs, the Flash button can be used to activate additional features, e.g. transfer of a call or pick-up of a call.

7. Redial

In the case of busy tone or no answer, you can redial the number. For this purpose, cradle the handset, lift it again and press the redial button.

8. Programming speed dial number

- Remove the plastic cover and the directory card.
 - Pick up the handset from the cradle, then press the STORE button.
 - Dial the number you wish to store. To program 'pause', press the REDIAL button.
 - Press the STORE button.
 - Press the Speed Dial button which you wish to store.
 - If an error is made while programming a number, place the handset on the cradle and then repeat steps from a).
 - Replace the plastic cover and the directory card.
- Each Speed Dial number can store a max of 32 digits. Pauses count as digits. If the telephone line is disconnected, speed dial numbers will be saved up to 10 years while disconnected.

9. Speed dial

Speed dial numbers are stored and may be dialed with the touch of a single button.

NEC America, Inc.

IMPORTANT SAFETY INSTRUCTIONS

When using your telephone equipment, basic safety precautions should always be followed to reduce the risk of fire, electric shock and injury to persons, including the following:

- Read and understand all instructions.
- Follow all warnings and instructions marked on the product.
- Do not use this product near water, for example, near a bathtub, wash bowl, kitchen sink, or laundry tub, in a wet basement, or near a swimming pool.
- Do not place this product on an unstable cart, stand, or table. The product may fall, causing serious damage to the product.
- Slots and openings in the cabinet and the back or bottom are provided for ventilation. To protect it from overheating, these openings must not be blocked or covered. The openings should never be blocked by placing the product on a bed, sofa, rug, or other similar surface. This product should never be placed near or over a radiator or heat register. This product should not be placed in a built-in installation unless proper ventilation is provided.
- Never push objects of any kind into this product through cabinet slots as they may touch dangerous voltage points or short out parts that could result in a risk of fire or electric shock. Never spill liquid of any kind on the product.
- To reduce the risk of electric shock, do not disassemble this product. Take it to a qualified serviceman when service or repair work is required. Opening or removing covers may expose you to dangerous voltages or other risks. Incorrect reassembly can cause electric shock when the product is subsequently used.
- Avoid using a telephone during an electrical storm. There may be a remote risk of electric shock from lightning.
- Do not use the telephone to report a gas leak in the vicinity of the leak.

NOTE: The 'H' switch setting for the receive volume control should only be used by hearing impaired individuals, otherwise hearing damage may occur. This telephone complies with HAC (Hearing Aid Compatible) volume control defined by section 68.317 of the FCC Rules and Regulations, 1996 edition.

Please keep this unit away from equipment that uses radio wave or microwave, a portable radio, a microwave oven, etc. This type of equipment may cause improper operation.

SAVE THESE INSTRUCTIONS

FCC Part 68 Registration

The equipment complies with Part 68 of the FCC Rules. A label which contains the FCC Registration Number and ringer equivalence number(REN) for the equipment, country of origin and model number among other information is located on the bottom of the equipment. If requested this information should be provided to the telephone company.

The equipment uses the following USOC jacks: RJ11C

KX -type telephone with message waiting and/or line status indicators may only be connected to host system and not to the Network.

The REN is used to determine the quality of the device which may be connected to the telephone line. Excessive REN's on the telephone line may result in the devices not ringing in response to an incoming call. In most, but not in all areas, the sum of REN's should not exceed five (5.0). To be certain of the number of devices that may be connected to the line, as determined by the total REN's contact the telephone company to determine the maximum REN for the calling area.

If the equipment causes harm to the telephone network, the telephone company will notify you in advance that temporary discontinuance of service may be required. If advance notice isn't practical, the telephone company will notify the customer as soon as possible. Also, you will be advised of your right to file a complaint with the FCC if you believe it is necessary.

The telephone company may make changes in it's facilities, equipment, operation or procedures that could effect the operation of the equipment. If this happens, the telephone company will provide advance notice in order for you to make the necessary modifications in order to maintain uninterrupted service.

If trouble is experienced with this equipment, please contact your NEC Dealer for repair and/or warranty information. If the trouble is causing harm to the telephone network, the telephone company may request you to remove the equipment from the network until the problem is resolved.

NO REPAIRS CAN BE DONE BY THE CUSTOMER.

The equipment is hearing-aid compatible.

CAUTION: The act of monitoring or recording telephone conversations under certain circumstances may violate federal or state statutes. Consultation with your legal counsel prior to engaging in such practices would be advisable.

FCC Part 15

Complies with the limits for a Class B computing device pursuant to Subpart J of Part 15 of FCC Rules.

INDUSTRY CANADA (CS-03)

The Load Number of the equipment: N/A

"Notice: The Industry Canada label identifies certified equipment. The certification means that the equipment meets certain telecommunication network protective operational and safety requirements. Industry Canada does not guarantee the equipment will operate to the user's satisfaction.

"Before installing this equipment, users should ensure that it is permissible to be connected to the facilities of local telecommunications company. The equipment must also be installed using an acceptable method of connection. In some cases, the company's inside wiring associated with a single line individual service may be extended by means of a certified connector assembly (telephone extension cord). The customer should be aware that compliance with the above conditions may not prevent degradation of service in some Situations.

"Repairs to certified equipment should be made by an authorized Maintenance facility designated by the supplier. Any repairs or installations made by the user to this equipment, or equipment malfunctions, may give the telecommunications company cause to request that the user disconnect the equipment.

Users should ensure for their own protection that the electrical ground connections of the power utility, telephone lines, and internal metallic water pipe system, if present, are connected together. This protection may be particularly important in rural areas.

Caution: Users should not attempt to make such connections themselves, but should contact the appropriate electric inspection authority, or electrician, as appropriate.

SAFETY CONSIDERATIONS:

This equipment complies with Underwriters Laboratories Standard U.L. 1459, Third Edition.

IMPORTANT BATTERY INFORMATION:

The product you have purchased contains a Lithium battery. The battery must be recycled or disposed of properly. At the end of its useful life, under various state and local laws, it may be illegal to dispose of this battery into the municipal waste stream. Check with your local solid waste officials for details in your area for recycling options or proper disposal.